

TLAR Series Molding Power Inductors Size 100760



FEATURES




- Compliant for 100% Lead(Pb)-Free and RoHS.
-
-
-

APPLICATION

-
-
-
-

Dimensions: [mm]

Land Pattern: [mm]




Electrical Properties:

Part No		Inductance (μH)	Resistance (mΩ)		Rise Current		Satura on Current		
	1		0.14	0.16	68		88		
			0.14	0.16	68		88		

All test data is referenced to 25 °C ambient.
 Saturation Current will cause L0 to drop approximately 30%.
 Temperature Rise Current: The actual value of DC current when the temperature rise is ΔT=40 °C.


Soldering Reflow:



Preheat condition: 150 ~200 / 60~120 sec.
 Allowed time above 217 : 60~150 sec.
 Max temperature: 260 .
 Time within 5 of actual Peak Temperature: 30 max. sec.

Packaging Information:

Tape Dimension:



A0 (mm)	B0 (mm)	D (mm)	P0 (mm)	P1 (mm)	W (mm)	K0 (mm)	E (mm)	T (mm)

Product Marking:

Marking	Printing (Inductance)
---------	-----------------------

Reel Dimension: [mm]



Cautions and Warnings:

Storage Conditions:

- The storage period is within 12 months after the completion of production. Be sure to follow the storage conditions (temperature: -5 to 35°C, humidity: 75% RH Max). If the storage period elapses, the soldering of the terminal electrodes may deteriorate. The warranty period is one year.
- Product should not be exposed to environment with high temperature, high humidity, dust, corrosive gas and etc.
- Products should be handled with care to avoid damage or contamination from perspiration and skin oils.
- Please always handle products carefully to prevent any damage caused by dropping down or inappropriate removing.

Operation Instructions:

- Self heating (temperature increase) occurs when the power is turned ON, so the tolerance should be sufficient for the set thermal design.
- Before soldering, be sure to preheat components. The preheating temperature should be set so that the temperature difference between the solder temperature and chip temperature does not exceed 150°C.
- Soldering corrections after mounting should be within the range of the conditions determined in the specifications. If overheated, a short circuit, performance deterioration, or lifespan shortening may occur.
- Generally, Koher might not be familiar with either customer's specific application or actual requests as customer does. As a result customer shall be responsible for checking and confirming whether Koher product with the performance described in the product specification is suitable for using in customer's particular application or not.